

**METER SOCKET WITH OVERHEAD SERVICE ENTRANCE  
3-PHASE, 3-WIRE, 480 VOLTS (UNGROUND), 0-200 AMPERES  
METERING SEQUENCE: METER-SWITCH-FUSE**

**Customer furnishes and installs:**

1. Company listed 5-terminal meter socket with center phase sliding link disconnect (see Note 1 and Sheet D-4).
2. Conduit and service entrance conductors.
3. Water-tight hub.
4. Metallic conduit shall be bonded to the meter socket.
5. 5th terminal. May be in the 6 or 9 o'clock position (6 o'clock shown, see Note 2).

**Company furnishes and installs the  
Watt-hour meter.**

**Notes:**

1. Provide 4" clearance around meter from all foreign objects.
2. When the 5th terminal is in the 9 o'clock position and the potential tap wire from the center phase to the 5th terminal is not provided by the manufacturer a #14 black insulated wire shall be installed.

