

## 5 & 7-TERMINAL SINGLE AND MULTI-POSITION METER SOCKETS WITH DIRECT BURIED UNDERGROUND SERVICE LATERAL

Service Application				<u>Reference</u>
3Ø	3-Wire	240(grounded) or 480 Volts	0-200 Amperes	M-18
3Ø	4-Wire	208Y/120 or 480Y/277 Volts	0-200 Amperes	M-19

Supplier	Single Position Socket Catalog Numbers			5th Terminal Catalog Number
	240 Volts, 3Ø	480 Volts, 3Ø	208Y/120 Volts, 3Ø 480Y/277 Volts, 3Ø	
	200 Amp.	200 Amp.	200 Amp.	
Cutler-Hammer	UT-H5213_-CH UTE5213_-CH	UT-H5213_-ND-CH	UT-H7213_-CH (6) UTE7213_-CH (6)	
Landis & Gyr/ Siemens (5)	HQ-5U-40405 CQ-5U-40605	HQ-5NDU-9804-8585 (1)	HQ-7U-40407 CQ-7U-40607	
Midwest	UT-H5213_-MEP	UT-H5213_-ND-MEP	UT-H7213_-MEP (6)	
Milbank	U9551	U8624(1)(2)	U7423 U9701	
Murray		RH173CR	RH173GR	
Square-D	UT-H5213_-SQD	UT-H5213_-ND-SQD	UT-H7213_-SQD (6)	
Multi-Position Socket Catalog Numbers				
Milbank			U2732-XT-PED (2 Pos) (3, 4)	

- (1) This socket has a center phase disconnecting link.
- (2) A9064 heavy-duty closure plate required.
- (3) S2291-TO pedestal required.
- (4) K1539 set screw connector kit required.
- (5) Add "S" prefix for Siemens.
- (6) Cover plate required; Catalog no. ARP00002-CH, ARP00002-MEP or ARP00002-SQD

## 5 & 7-TERMINAL SINGLE POSITION METER SOCKETS WITH AC NETWORK UNDERGROUND SERVICE LATERAL (OUTDOOR INSTALLATIONS ONLY)

Service Application				<u>Reference</u>
1Ø	3-Wire	208Y/120 Volts	0-100 Amperes	M-18
3Ø	4-Wire	208Y/120 Volts	0-200 Amperes	M-19

Supplier	Socket Catalog Numbers			5th Terminal Catalog Number
	208Y/120 Volts, 1Ø		208Y/120 Volts, 3Ø	
	100 Amp.	200 Amp.*	200 Amp.	
Cutler-Hammer		UT-H5213_-CH UTE5213_-CH		
Landis & Gyr/ Siemens (5)	UAT111-_P (1)(4)	HQ-5U-40405 CQ-5U-40605 UAT417-_P (1)(4)	HQ-7U-40407 CQ-7U-40607	(1) 659-0121
Midwest		UT-H5213_-MEP		
Milbank	U1773 (2)	U9551	U9701	(2)K5T
Murray		RH173CR RS192A (3)	RH173GR	(3)RX012
Square-D		UT-H5213_-SQD		

**\*Maximum service size is 100 amperes. A 200 ampere socket is required for adequate space to terminate the service lateral cable.**

- (1) thru (3) see 5th Terminal Catalog Number column.
- (4) Use coverplate 38595-1 when required.
- (5) Add "S" prefix for Siemens.