

**4 & 5-TERMINAL SINGLE AND MULTI-POSITION METER SOCKETS
WITH CONCRETE ENCASED UNDERGROUND SERVICE LATERAL
(NOT FOR AC NETWORK)**

Service Application				Reference
1Ø	3-Wire	120/240 Volts	0-200 Amperes	M-17
3Ø	3-Wire	240 Volts (grounded)	0-200 Amperes	M-18

Supplier	Socket Catalog Numbers*		
	120/240 Volts, 1Ø		240 Volts, 3Ø
	100 Amp.	200 Amp./Pos.	200 Amp.
Cutler-Hammer	UHT-RS111B-CH (5)	UHT-RS213B-CH (5) UT-H4213B-CH (5) UTE4213B-CH (5)	
Landis & Gyr/ Siemens (4)	UA2311-_P (2 Pos.) (1) UA3311-_P (3 Pos.) (1) UA4311-_P (4 Pos.) (1) UAT111-_P (1)	HQ-4GU-40404 CQ-4U-40604 UA2716-_P (2 Pos.) (2) UAT417-_P (1) UA2717-_P (2 Pos.) (2) UA3717-_P (3 Pos.) (2) UA4719-_P (4 Pos.) (2) UA5719-_P (5 Pos.) (2) UA6719-_P (6 Pos.) (2)	HQ-5U-40405 CQ-5U-40605
Midwest	UHT-RS111B-MEP (5)	UHT-RS213B-MEP (5) UT-H4213B-MEP (5)	
Milbank	U7588	U9551 U2872 (2 Pos.) (3) 200A U2873 (3 Pos.) (3) <u>270A</u>	U9551
Murray		RH173CR	
Square-D	UHT-RS111B-SQD (5)	UHT-RS213B-SQD (5) UT-H4213B-SQD (5)	

***The main bus ampere rating is indicated for each multi-position listing. The underlined rating is restricted due to the largest service lateral that can be terminated in the unit.**

- (1) Coverplate 38595-1 to cover hub opening required.
- (2) Use coverplate 56933 when required to cover hub opening, 2 required for 5 & 6 pos. sockets.
- (3) K1539 set screw connector kit required.
- (4) Add "S" prefix for Siemens.
- (5) Cover plate required; Catalog no. ARP00002-CH, ARP00002-MEP or ARP00002-SQD

**JOINT USE TERMINATION PEDESTAL
FOR COMMUNICATIONS EQUIPMENT WITH DIRECT BURIED SERVICE**

Supplier	Catalog Numbers
Milbank	U4329-O(1)

(1) This unit is intended to work with all manufacturers' metering pedestals.