

Part 3: Equipment Control

310.50.30) All keys for the device 69 keyed permissive switch must be given to the We Energies Start-Up Engineer after the Customer has proven to the Start-Up Engineer the operation of the circuit breaker or interrupter switch control circuits prior to placing the substation in service. All of the keys will be retained by We Energies

310.60) Miscellaneous Devices

Additional control circuit requirements are as follows:

310.60.10) All indicating lamps shall be color coded to indicate the functions of the lamps, as specified below:

| Color | Function |
|--------|------------------|
| Red | Close |
| Green | Open |
| Blue | Alarm |
| Orange | D-C Potential |
| White | A-C Potential |
| Clear | Ground Detection |

310.60.20) All circuit breaker trip circuit fuses shall be monitored with indicating lamps or alarm relays.

320) Automatic Transfer Control for Switchgear and Circuit Breakers

The following are items pertain specifically to the installation and utilization of automatic transfer and control equipment. Any new control package must be carefully reviewed by We Energies to evaluate equipment integrity for the purpose of protecting the customer service reliability, and to protect the We Energies distribution system, minimizing disturbances to other customers. Additional requirements relative to supply conductor terminations, grounding provisions for supply conductors, service disconnected means, overcurrent protective devices, surge protection, interlock systems, and metering facilities are contained in Parts 1 and 2 of this book.

320.10) Position and Transfer

320.10.02) An open transition transfer scheme shall be incorporated into the control scheme to guarantee that during an automatic source transfer the incoming lines will not be tied together.

320.10.04) A loss-of-source voltage timer is necessary to delay source transfer and establish that the loss of source is not a transient condition. This will mitigate unnecessary switching. The loss-of-source (voltage) timers must be adjustable in a minimum 1–10 second range to allow for coordination with upstream We Energies protective devices.

Part 3: Equipment Control

320.10.10) Switch Operators and Breakers

- a) The switch operators or breakers must be provided with a method to mechanically (manually) operate, which is not dependent upon the control package electrical system.
- b) The switch operators or breakers must be a stored energy type so that one operation, either to open or to close can be done after loss of supply voltage.
- c) The switch operators or breakers must have targets to indicate its position (open/closed) and the operator status (charged/discharged and coupled/decoupled).

320.10.20) Switchgear Only Requirements

- a) Switch operators must have a provision for padlocking in both open and closed positions.
- b) The switch operator must be capable of being manually decoupled. The decoupled state must be visibly evident through some mechanically altered condition.
- c) The doors to the service switch bays and tie bay for live front equipment must be interlocked to the switch operators so that automatic and manual operation is blocked if any of the doors are open.
- d) It must not be possible to couple the operator to the switch if both are not in the same open/closed position, in such a manner that the position of either operator or switch indicates incorrectly.

320.10.30) Circuit Breaker Only Requirements

a) Two Lines Serving a Common Load with Automatic Transfer:

One set of overcurrent relays may be used for both lines' circuit breakers provided that the relays will not be affected during a time when We Energies may be performing closed transition switching as described above.

b) Two Lines Serving Separate Loads With Automatic Transfer:

b.1) This system may be operated with both line circuit breakers normally closed and the bus tie circuit breaker normally open, or with one line circuit breaker closed and the bus tie circuit breaker normally closed and the remaining line circuit breaker normally open.

b.2) The circuit breaker control circuits shall be arranged so that the three circuit breakers (two line breakers and one bus tie breaker) cannot be normally closed at the same time.

Part 3: Equipment Control

Keyed permissive switch contacts shall allow only We Energies to defeat this scheme to perform closed transition switching during abnormal power system conditions.

320.10.40) Preferred/Alternate Source Selection

- a) The control scheme must allow for field adaptation for selection of the preferred source.
- b) The control shall not allow the switchgear to automatically return to the preferred (normal) source after having been transferred to an alternate source. Source return shall be made only by We Energies personnel. The equipment may automatically return to the preferred supply if the alternate supply is de-energized and the preferred supply has been restored.

320.20) Indicating Features

Indicating lamps shall be provided to monitor both normal and alternate line potential conditions.

320.30) Sensing

320.30.10) If installed on the 26.4 kV subtransmission system, over/under voltage sensing must be adjustable to compensate for future conversion of primary voltage from 26.4 kV subtransmission to 24.9Y/14.4 kV distribution.

320.30.20) Potential transformers supplying control power or voltage sensing must have removable high and low voltages fuses. They must be We Energies approved devices since they are directly connected to We Energies lines.

330) Switchgear or Circuit Breaker with Manual Transfer

330.10) Two Lines Serving A Common Load With Manual Transfer

One set of overcurrent relays may be used for both lines' circuit breakers provided that the relays will not be affected during a time when We Energies may be performing closed transition switching during abnormal system configurations.

330.20) Two Lines Serving Separate Loads With Manual Transfer

330.20.10) This system may be operated with both line circuit breakers normally closed and the bus tie circuit breaker normally open, or with one line circuit breaker closed and the bus tie circuit breaker normally closed and the remaining line circuit breaker normally open.